

XLR2POLYX Installation

XLR2POLYX connects your external wireless microphone receiver with XLR output such as Sennheiser, AKG, Audio Technica, Shure, ... into Poly Studio X50, Studio X52, Studio X70 and Poly Studio USB devices.



Installation

- XLR F - to the output of your wireless mic receiver
- RJ45 - to extension microphone input on your Poly Studio unit

It is important to place the XLR2POLYX unit in close proximity to the Poly Studio. Use the brackets to hang the unit behind your display (“letters” above the edge.) This is because the XLR2POLYX unit monitors the activity in the room using its internal microphone to ensure seamless switching between the wireless mic connected via the XLR2POLYX unit and the Poly Studio unit's internal microphones.



Speech from your wireless microphone is transmitted to the remote side, it is not played back locally.

Your Poly Studio X configuration

1. In the system web interface, go to **Audio/Video > Audio > General Audio Settings**.
2. Select the **Enable Auto Mic Switching** check box (your changes save automatically).